

PT-580

PROGRAM TIMER

Product Features

- ❑ 8-Channel Program Input.
- ❑ Broadcast the reservation audio files that stored in the SD cards on scheduled time.
- ❑ Support WAV, WMA, MP3 high quality music / audio source broadcast and recording.
- ❑ Program configuration thru SD card and software.
- ❑ Zone trigger control by software.



Technical Specifications

Features	8-Channel Program Timer
Audio Input	LINE: -10dBV balanced / 10kΩ MIC / LINE: -50dBV balanced / 10kΩ
Audio Output	Balanced Line: +4dBV / 500Ω Unbalanced Line: 0dBV / 1kΩ
Frequency Response	100 – 20k Hz, ±3dB
SNR	MIC: -65dBu LINE: -75dBu
THD	< 0.05%
Power Supply	220V AC 50/60Hz, 24V DC
Dimension (W x D x H)	482mm x 100mm x 44mm
Weight	1.72 kg