Product Features

PMC-1001

DIGITAL PAGING CONSOLE

- ☐ Control distance between PMC-1001 and ZS-1012 is up to 500m
- ☐ Up to 8 units PMC-1001 can be cascaded
- ☐ Using RJ45 port to transfer audio signal
- ☐ Each PMC-1001 can control up to 8 units of ZS-1012
 - 12-Zone switches control with LED indicator
- Condenser gooseneck microphone adorned with illuminated ring



Technical Specifications

Audio Output Signal	1.5V
Power Consumption	5W
Frequency Response	16Hz – 12kHz
Power Supply	24V DC @ 500mA
Dimensions (W x D x H)	245mm x 172mm x 73mm
Weight	1.6kg